


J1	J2	J3	J4	J5	WIRE			
DT06-12SB-CE06	DT06-12SA-CE06	DT06-4S	DT06-4S	DT06-2S	TWISTED PAIRS	ID	COLOR	AWG
1			2		TWISTED PAIRS	0V	BLACK	18
12			1			POWER	RED	18
2			4		TWISTED PAIRS	CAN LO	GREEN	18
11			3			CAN HI	YELLOW	18
3		2			TWISTED PAIRS	0V	BLACK	18
10		1				POWER	RED	18
4		4			TWISTED PAIRS	CAN LO	GREEN	18
9		3				CAN HI	YELLOW	18
6	12				TWISTED PAIRS	CAN LO	GREEN	18
7	11					CAN HI	YELLOW	18
5	2				TWISTED PAIRS	0V	BLACK	18
8	1					POWER	RED	18
				2	TWISTED PAIRS		ORANGE TO RED	18
	8			1			BROWN	18

CONNECTOR	FUNCTION
J1	CAN A Connector on Console TAG I/O Contoller
J2	To Grayhill Display or Eaton Display Adapter P# ALCTC-001-H10
J3	Left Joystick
J4	Left Monitor Control Key Pad
J5	Breathing Air Sensor

SECTION	LENGTH(INCH)
L1	1.5
L2	5
L3	16
L4	17
L5	14.5

		FINISH:		DEBUR AND BREAK SHARP EDGES		DO NOT SCALE DRAWING		REVISION	
		DRAWN: CJ		DATE: 01/08/2019		<b>621 Technologies inc.</b> <b>PLATFORM HARNESS ALCTC-001-H4</b>			
CHK'D									
APPV'D									
MFG									
Q.A				MATERIAL:		DWG NO.		A3	
				WEIGHT:		SCALE:2:1		SHEET 1 OF 1	